ULTRON LIGHTING & BEYOND





Low Bay Canopy - Mammoth Series



Description

Altech's Mammoth Series Low Bay Canopy has a 10-year wraparound warranty. It is perfectly suited to illuminate low canopy settings.











Applications

Warehouses Low Ceilings Hallways Parking Garages Underpasses Tunnels

Details

IP Rating IP67

Materials Die Cast Aluminum

Lens Polycarbonate

L70 Life 150,000 Hours

Warranty 10 Years

CRI 80+

Qualification UL, DLC 5.0, FCC, CE, RoHS

Chip Man. Philips

Electrical

Power Factor 0.99
Frequency 50/60 Hz
Max THD 15%

Operating Temp. -40° F to 130° F -40° C to 54° C

Dimming 0-10V

MODEL/DLC #:	U-LPCN-28-50	U-LPCN-40-50	U-LPCN-60-50	U-LPCN-90-50	
Color Temp:	5000K 5000K		5000K	5000K	
Input Wattage:	28W	40W	60W	90W	
Lumens:	3,584 lm	5,040 lm	7,800 lm	11,880 lm	
Equivalent:	100W MH	175W MH	200W MH	250W MH	

Ordering Information


Example: U-LPCN-60-50-130-1-1-F-WP(3)-BZ

Item	Wtg	Color Temp.	Lumen Package	Distribution	Input Voltage	Mounting	Options	Finish
U-LPCN	28	30 - 3000K	130 - 130 lm/W*	1 - 120°*	1 - 100-277V*	F - Flush*	MS - Motion Sensor	BZ - Bronze*
	40	40 - 4000K			2 - 480V	P - Pendant Adaptor	,	BL - Black
	60	50 - 5000K*					(X)P - (X)-Pin Twist-Lock Base	W - White
	90	57 - 5700K					(X = select one: 3,5, or 7)	GR - Gray
							WP(X) - Additional Whip	SP - Other
							(X = specify total length in	
							ft.; 2.67' is standard)	***

Standard

Additional Notes

- 4000K and 5000K, 100-277V are stocked locally, check for ETA's
- Step-down dimming motion sensors are for 100-277V models only
- · Additional charges apply for items under "Options" column and non-standard colors
- Additional knockout holes available on all 4 sides upon request
- Not all product variations listed on this page are DLC Qualified. To ensure that a specific model is qualified, visit www.designlights.org/search.









System Watts	ССТ	Lumens	lm/W
	3000K	3,484	124
	4000K	3,556	127
28	5000K	3,584	127
	5700K	3,612	129
	3000K	4,862	122
	4000K	4,960	124
40	5000K	5,040	126
	5700K	5,080	127
	3000K	7,473	125
	4000K	7,680	128
60	5000K	7,800	130
	5700K	7,860	131
	3000K	11,365	126
00	4000K	11,700	130
90	5000K	11,880	132
	5700K	11,970	133

Accessories and Options



Phenix Internal Emergency Inverter (18470X-2) (optional)




Multi-Level Motion Sensor (optional)



3/4" Threaded Pendant Adaptor (optional)

Fixture Dimensions and Weight




Length	Width	Height	Weight
12 in.	12 in.	3.94 in.	6 lb.
304 mm.	304 mm.	100 mm.	2.7 kg.

Installation

- Disconnect all power sources (VERY IMPORTANT).
- Mount the back plate onto the ceiling 2.
- Connect the input and ground wires of the fixture to the power supply. Brown is live. Blue is neutral. Green/Yellow is ground.



- Slide fixture on the mounting plate
- Tighten screws



Pictured: LPCN mounting plate

Maintenance

This luminaire is designed to last for years with minimal care. For optimal performance, periodically clean the lens, with a mild, non-abrasive glass cleaner and soft cloth. DO NOT use solvents or cleaners containing abrasive agents. When cleaning the luminaire, make sure to have the power turned off and do not spray liquid cleaner directly onto the LED chips, socket, or wiring.

